QUICK START

Microphone module

sp-mcp_mdp · at the station

SHOOMS

QS-MC-EN · 09.2026

BEFORE YOU START

Work is done with the 12 V line unpowered. Only SHOOMS staff open the module's enclosure.

INSTALLATION STEPS

1. Set up the stand and fix the module, the microphone and the repeat button on it.
2. Screw on the Wi-Fi antenna.
3. Connect the microphone to the «МІКРОФОН» connector and the button to the «КНОПКА» connector.
4. Connect the 12 V power to the input connector; if the line continues, connect it to the second power connector.
5. Apply power: the display should light up and the module should appear in the SHOOMS system.
6. Together with a SHOOMS specialist, test the shooter's command, shot detection and the repeat button.

BEFORE YOU LEAVE

- [ ] Module, microphone and button fixed on the stand
- [ ] Antenna screwed on
- [ ] Microphone and button cables in their connectors
- [ ] 12 V line connected, and the next station too
- [ ] Display lit, module visible in the system
- [ ] Command, shot and repeat button tested

IF SOMETHING DOES NOT WORK

The display is dark	The 12 V line and the power connectors on this and the neighbouring modules
No command is recognised	The «МІКРОФОН» connector and the cable along its whole length
Commands are recognised intermittently	The windshield and the microphone's distance from the shooter
The repeat button does nothing	The «КНОПКА» connector and the button cable

The full user manual is in the documentation set or behind the QR code. SHOOMS support: support@shooms.net